## How To Interface PSD Logistics With Lenel OnGuard

## Last Updated 20/12/2022

## Solution

1) Log into the PSD Logistics Manager.

2) Select "Settings" -> "Access Management Software". This will display the Access Management Software Settings window.

Access Management Software Settings	×
🗐 🗠 🕕 🛷	
Access Management Software           Software Name         None           No Software Selected         None	•
	Save Close Help

3) Select Lenel OnGuards from the Software Name drop down list.

Enter the hostname or IP address of the server running the Lenel OnGuard services.

Access Management Softv	vare Settings	×			
🗄 🗠 🕕 🤣					
C Access Management	Software				
Software Name	Lenel OnGuard 👻				
Main Open Acce	Main Open Access Signalling Card Access Events Misc				
Lenel OnGuard Se					
<ul> <li>Host Name</li> </ul>	PSD-OFFICE4   Local Host Ping				
O IP Address					
	Save Close Helo				

Select the Open Access tab sheet and enter the Lenel OnGuard super user login details to be used by PSD Logistics. Leave everything else set to their default values.

cess management 50	Dreware			
tware Name	Lenei Unguard	•		
lain Open Access	s Signalling Car	d Access E	vents Mis	ю.
Lenel OnGuard Ope	n Access			
URL	/api/access/onguard	l/openacces:	s	Default
Port		8080 🗘		Default
Application ID	63920823-c727-4a4c	l-a8a6-5c806	5c9ecda	
Login Name	sa			
Password	*****			
Session Reset		4 🗘	Hours	Default
Session Renew		6 🗘	Minutes	Default
Subscription Reset		4 🗘	Days	Default
Subscription Renew		10 🗘	Seconds	Default
	Test			
		Sa		lose Hel

Select the Signalling tab sheet and set everything to their default values.

Access Management Software S	Settings	×			
🗄 🗠 🕕 🤣					
Access Management Software					
Software Name Le	nel OnGuard 🗸 🗸				
Main Open Access Signalling Card Access Events Misc					
PSD Logistics Signallin	ng				
PSD Logistics Port	2152 🗘	Default			
Review Lines	10000 🗘	Default			
	Save	Close Help			

Select how frequently Card Access Events should be queried. Once an Hour is the recommended setting.

Access Management Software Settings	×
🔚 🕫 🕕 🤣	
Access Management Software       Software Name   Lenel OnGuard	
Main     Open Access     Signalling     Card Access Events       Query Card Access Events     O       Never       O Once an Hour	
Unce a Day at	
Save Close Help	

Select the Misc tab sheet and set everything to their default values.

Access Management Softwa	re Setti	ngs	×
🖩 🗠 🕕 🤣			
C Access Management Sc	oftware	)	
Software Name	Lenel (	DnGuard 🗸	
Main Open Access	s ( S	ignalling Card Access Events Misc	
Photo ID Dimensions		240 ♀ H 240 ♀ W	
Time Zone		8.0 🗘 Hours G.M.T.	
Query People At	<b>V</b>	12:30 AM 👻	
Query Last Modified	<b>V</b>	5 🗘 Minutes	
Query Current Locations	<b>~</b>	5 🗘 Minutes	
Errors E-mail Group		None 👻	
Export HTTP Data			
Use Card For Live Events	<ul><li>✓</li></ul>		
		Save	Help

Select "Save" and "Close".